



# Characterization of an In-Situ Ground Terminal via a Geostationary Satellite

**Marie Piasecki\*, Bryan Welch\*, Carl Mueller\*\***

*\*NASA Glenn Research Center  
Cleveland, OH 44135*

*\*\*Vencore, Inc.  
Chantilly, VA 20151*

October 15, 2015



# Introduction



- Space Communications and Navigation (SCAN) Testbed launched in 2012 as external payload aboard the International Space Station (ISS)
  - Early testing of Earth-facing antenna showed operational limitations for communication links with Wallops Ground Station
- In 2013, the Space Communications and Navigation (SCaN) project decided it was necessary to build their own specialized ground station
- Ground Station Requirements
  - Facilitate testing novel communication technologies
    - Experimenter provided radios with Cognitive Engines
    - Multi-Node Networking applications
  - Also serve as link between Tracking and Data Relay Satellites (TDRS) and Ground Integration Unit
  - Fully Characterized System
    - Extensive component testing
    - Validation of results after installation
    - Monitor potential System degradation over time

**In early winter 2015, the SCaN Testbed Glenn Research Center S-Band Ground Station (GRC-GS) was completed to provide this service.**



# Overview




- Short description with a focus on design choices for a characterization
  - System hardware design and GUI information
- Pre-installation testing
  - Description and an example subsystem
  - Additional information on antenna testing
- Post-installation Validation
  - Methodologies and data related to subsystem discussed in pre-installation
  - In-depth discussion of use of a geostationary satellite for antenna validation with comparison to range testing
- Lessons Learned



# GRC Ground Station



- S-Band (2.0 – 2.4 GHz)
- Equipment located in 2 buildings
  - Building 110 (B110) - Amplifiers, Antenna, Attenuators, Filter Banks, Couplers
  - Building 333 (B333) – Amplifiers switches, Channel Simulator, Couplers
- Communicates with SCAN Testbed and TDRS
- Future validation and monitoring considered in the design
  - 12 Couplers - Power meters
  - 2 Couplers - Spectrum Analyzers
  - Loopback Mode





# GRC Ground Station Graphical User Interface



- Messages
- **Logging**
- Load in predictions for received power levels
- Filter Bank Switches
- Radio Switches
- **Pass-through/Loopback Switch**
- Channel Simulator Switch
- **Power Meters**
- Attenuators
- **Power Supply Current Draw**
- **Temperature Sensors**
- **Power Amplifier Feedback**
- Predicted Power at the Feed

RF\_Monitor - Version 1.3

Messages: Successful Startup - 24/24 Devices

Log File Name: [ ]

STAT Prediction File: [ ]

Power Amplifier Status: Transmit Disable, Attenuation 20, RF Power N/A

TX Frequency: Select Frequency, Freq (MHz) [ ]

TX Radio: Select Radio, TX Channel Sim: Inline ☐ Bypass ☒

Transmit Settings - Disabled

Open Block Diagram

Logging

Load STAT File

RX Frequency: Select Frequency, Freq (MHz) [ ]

☐ RX Unfiltered

RX Radio: Select Radio, RX Channel Sim: Inline ☐ Bypass ☒

Receive Settings - Disabled

Power Meter Color Info:  
-Yellow- Exp: Val Pred < -35.00 Act: Diff from Exp > 3.00  
-Red- Exp: Val Pred < -40.00 Act: Diff from Exp > 5.00  
-Cyan- Exp: Unknown - Based on Power Meter reading Unknown signal Level Act: Unknown - Reading beyond Power Meter Threshold

Expected Actual B333

CHANNEL SIM	
Power Meter 1	N/A -36.05
Power Meter 2	-0.59 -35.31

Expected Actual B333

CHANNEL SIM	
Power Meter 12	-25.80 -24.02
Power Meter 11	-103.51 -63.90

Expected Actual B333

RS SPECTRUM ANALYZER	
Power Meter 11	63.00 -17.18
Power Meter 12	-35.88

Expected 1 Actual 1 Expected 2 Actual 2 Expected 3 Actual 3

Power Supply 1 Current	
Expected 1	1.904
Actual 1	1.903
Expected 2	0.075
Actual 2	0.072
Expected 3	0.135
Actual 3	0.119

Expected Actual B110

FILTER BANK	
Power Meter 3	-35.40 -35.54
Power Meter 4	-43.24 -37.15
Power Meter 5	-84.60 -26.29

Expected 1 Actual 1 Expected 2 Actual 2 Expected 3 Actual 3

Power Supply 2 Current	
Expected 1	1.474
Actual 1	1.488
Expected 2	0.15
Actual 2	0.143
Expected 3	0.27
Actual 3	0.241

Temperature: 71.45 Degrees Farenheit

RX Enclosure	
Power Meter 6	-33.34 -29.58
Power Meter 10	-60.75 -34.84

Temperature: 59.30 Degrees Farenheit

TX Enclosure	
Power Amplifier	0 N/A
Power Meter 7	21.69 -17.97

Temperature: 59.30 Degrees Farenheit

Antenna	
TX Power Radiated	-21.03
Power Meter 8	N/A -48.82

Calculated Power Meter 8

Predicted RX Power at the Feed








# Overall Testing Description



- Passive Components
  - Cables, filters, diplexers, couplers, adapters, and switches
  - S-Parameter Measurements
- Active Components
  - Amplifiers and Fiber Converters
  - S-Parameters, Gain, Noise Figure, Phase Noise, Intermodulation Distortion
- Antenna Testing
  - 2.4m Parabolic Reflector and circularly polarized Feed
  - Antenna pattern and Gain



- Testing Example – Filter Bank
  - Includes cables, switches, and filters
  - Each component was measured separately using a VNA
  - Components assembled into a filter bank and then re-measured
  - New measurement compared with cascaded component measurement




# Testing - Antenna

- Antenna arrived in 3 sections
- Assembled inside the Glenn Research Center Near Field Range
- Mounted to testing Pedestal
- Calibrated Horn used to quantify system performance
  - 50cm between antenna rim and probe
- Pattern Measurement Data taken

Characteristic	Value
Frequency	S-Band
Diameter	2.4m
Polarization	LHC
Half-Power Beamwidth (HPBW)	3.9°
Gain	31.5 dB

## Vendor Specifications



*Before and after pattern measurement the surface was scanned with Leica Geosystems LR200 Laser Radar to monitor potential warping*






# Testing - Antenna

- Pattern Measurements
  - Scanned at each operational Frequency
    - 2041.027 MHz, 2106.406 MHz, 2216.500 MHz, 2287.500 MHz
  - Data processed by the Nearfield Systems NSI2000 software
    - Transforms Near-field Measurements into a Far-field Pattern
    - 60° to Azimuth (Az) and Elevation (El) with 201 points in each dimension



# In-Situ Testing Components

- Pass-Through
  - Radio Frequency (RF) Signals inserted into signal chain to compare against laboratory cascaded measurements




- Loopback
  - TX and RX chains Connected together
  - Insert signal in TX chain at the radio

- Testing Setup



- TDRS contacts to measure Pattern
  - TDRS-Spare (TDRS-6)
  - TDRS-East (TDRS-9)
  - Excellent availability
  - Geostationary Orbit

- Gimbal Pointing

- Cannot go below  $10^\circ$  above the horizon
- Rate of motion
  - $20^\circ/\text{s}$  in Az
  - $4^\circ/\text{s}$  in El
- Hard Stops
  - $210^\circ$  and  $-210^\circ$  in Az
  - $90^\circ$  and  $-90^\circ$  in El
- Controlled via the LynxCAT toolset





## Spiral Track Testing






## Fixed Offset Testing








# In-Situ vs Nearfield Results





# Results at each Frequency





# Lessons Learned



- Importance of including monitoring and validation in the initial design
  - Very difficult to include after the fact
  - Lower margin built into the link budget
  - Cost savings
  - Reduces need to disassemble and re-test components
- Various uses after installation
  - Vital for troubleshooting
  - Useful for experimenters for tracking
  - Logging also useful for spectrum coordination
- Usefulness of using a geostationary satellite for validation
  - Verification of the integrity of the antenna after installation
  - Comparison between laboratory and in-situ environments
- Challenges
  - Local interferers – area TV broadcasters
    - Coordinate a “quiet” time for testing
    - Take multiple measurements and average



# Acknowledgement and References



The authors would like to thank the SCaN Testbed Project for its support in funding the design and construction of this station, as well as to the SCaN Testbed Mission Operations Team for their efforts in coordinating TDRS events directed to the NASA Glenn Research Center to enable this type of testing to be performed for the first time.

## • References

- M. Piasecki, "SCaN Testbed Glenn Research Center Ground Station Description, Performance, and Interface Document," NASA GRC-CONN-DOC-1073.
- [2] C. Balanis, Antenna Theory, 3rd ed. Vol. 1. John Wiley & Sons, 2005.
- [3] Antenna and Optical Systems Nearfield Range. NASA Glenn Research Center. <https://aos.grc.nasa.gov/test-facilities/near-field-range/> (August 2014).
- [4] B. Welch, M. Piasecki, M. Shalkhauser, J. Briones. "On-orbit Characterization of SDRs on ISS Utilizing Antenna Off-Pointing Capabilities on the SCaN Testbed," 37th Annual Antenna Measurement Techniques Association Meeting and Symposium, Tuscon, AZ. pp. 297-301, 2014.
- [5] B. Welch, "SCaN Testbed Radio Frequency Hardware Interface Description Document," NASA GRC-CONN-DOC-1024.
- [6] D. Schrage, "LynxCAT SK Users' Guide," NASA GRC-CONN-DOC-0982.
- [7] D. Chelmins, B. Welch. "Comparing On-Orbit and Ground Performance for an S-Band Software-Defined Radio," International Astronautical Congress. GRC-E-DAA-TN18125. (2014).